

PRODUCT DATASHEET

Starters for single operation at 230 V AC (ST 111, ST 171, ST 173) | Starters for single operation at 230 V AC



Areas of application

- Device for luminaire installation

Product benefits

- Supports large luminaire groups and long control lines
- Cascadable

Product features


- Signal amplifier for 1...10 V controllers and sensors
- Load capacity of the signal output: max. 100 mA

TECHNICAL DATA

Electrical data

Nominal wattage	2.00 W
Nominal voltage	220...240 V
Mains frequency	50/60 Hz

Dimensions & Weight



Product weight	187.00 g
----------------	----------

Temperatures & operating conditions

Ambient temperature range	0...+50 °C
---------------------------	------------

Additional product data

Mercury content	0.0 mg
-----------------	--------

Capabilities

Dimmable	Yes
----------	-----

Certificates & Standards

Type of protection	IP20
--------------------	------

Country-specific categorizations

Order reference	DIM SA DIM
-----------------	------------



Energy labelling regulation data acc EU 2019/2015

Length	189.00 mm
Height	30.00 mm
Width	30.00 mm

EQUIPMENT / ACCESSORIES

- Suitable for up to 100 electronic control gears
- Suitable for up to 33 signal amplifiers DIM SA

DOWNLOAD DATA

Documents and certificates		Document name
	User instruction / safety instructions	596700_Operating instructions DIM SA (GB)
	Declarations of conformity	334828_Declaration of conformity – DIM SA

LOGISTICAL DATA

Product code	Packaging unit (Pieces/Unit)	Dimensions (length x width x height)	Gross weight	Volume
4008321097095	Folding box 1	192 mm x 35 mm x 35 mm	199.00 g	0.24 dm ³
4008321097101	Shipping box 40	370 mm x 200 mm x 240 mm	8560.00 g	17.76 dm ³

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

DISCLAIMER

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.