

# PRODUCT DATASHEET Conversion kit + SubstiTUBE T8 EM Adv 20.6 W/4000 K 1500 mm

SUBSTITUBE ADVANCED Conversion Kit single lamp | LED tubes for electromagnetic control gear (CCG) including conversion kit for single lamp luminaires



#### Areas of application

- General illumination within ambient temperatures from -20...+50 °C
- Illumination of production areas
- Traffic zones and corridors
- Supermarkets and department stores
- Industry

#### **Product benefits**

- Only around 5 minutes per luminaire needed for rewiring
- No ECG compatibility issues
- No ECG maintenance necessary
- No bending thanks to glass tube
- Energy savings of up to 64 % (compared to T8 fluorescent lamp on CCG)
- Instant-on light, therefore ideally suitable in combination with sensor technology
- Very high resistance to switching loads
- Also suitable for operation at low temperatures

#### Product features

- Contains 10 SubstiTUBE T8 EM Advanced LED tubes and 10 conversion kits for single-lamp luminaires
- Conversion kit contains all necessary material for conversion of ECG luminaires to AC mains



- Detailed step-by-step instruction for guaranteed TÜV-certification available
- LED replacement for classic T8 fluorescent lamps with G13 socket for use in CCG luminaires or on AC mains
- Low flicker according to EU 2019-2020 (SVM  $\leq$  0.4 / PstLM  $\leq$  1)
- Single and tandem operation on conventional control gear (0.6 m version)
- Tube made of glass
- Mercury-free and RoHS compliant
- Uniform illumination
- Type of protection: IP20

# TECHNICAL DATA

## Dimensions & Weight

Product weight	2550.00 g

# Additional product data

Product remark	This product contains the following LED Tube as a light source: SubstiTUBE T8 EM Advanced 20.6 W/4000 K 1500 mm, EAN: 4058075611870, LED tube EEC: D / EPREL ID LED Tube: 563378
----------------	--

#### Certificates & Standards

# Country-specific categorizations

Order reference LEDTUBE T8 EM A
---------------------------------

# Safety advice

- Not suitable for operation with electronic control gear.
- Operation in outdoor applications in suitable damp-proof luminaires possible according to data sheet and installation instruction.

## DOWNLOAD DATA

	Documents and certificates	Document name
PDF	Extended installation guide	LEDVANCE LED TUBE Conversion Kit – Rewiring Instruction for 1-lamp luminaires

## **DISCLAIMER**

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.