

PRODUCT DATASHEET SMART+ BT Solar Spot Light RGB + TW

Smart+ Solar Spot Multicolor | Outdoor Smart Solar Spot & Bollard



Areas of application

- Outdoor use (IP44)
- Gardens
- Patios, balconies

Product benefits

- Easy and quick installation
- Colorful garden lighting with smart and intelligent control options
- Demand based lighting and energy saving thanks to daylight sensor
- High-quality materials
- Flexible mounting, also without use of ground spikes

Product features

- Solar powered outdoor LED luminaire
- RGB color control, approx. 16 million color options adjustable
- Dimmable
- Battery charging via solar panel
- Network protocol: Bluetooth
- Type of protection: IP44
- Controllable via SMART+ App (with minimum Android 8.0 or iOS 14.0)



TECHNICAL DATA

Electrical data


Nominal wattage	0.60 W
Nominal voltage	3,7 V
Nominal current	160.000 mA
Power factor λ	> 0.5
Protection class	11

Photometrical data

Luminous flux	45 lm
Total luminous flux of contained light sources	60 lm
Luminous efficacy	75 lm/W
Color temperature	30006500 K
Light color (designation)	Tunable White / RGB
Color rendering index Ra	> 80
Standard deviation of color matching	6 sdcm
Flickering metric (Pst LM)	-
Stroboscope effect metric (SVM)	
Photobiological safety group acc. to EN62778	RG0
Beam angle	58.00 °

Dimensions & Weight

Length	92.00 mm
Width	245.00 mm
Height	348.00 mm
Product weight	438.00 g



Materials & Colors

Product color	Black	
Housing color	Black	
Body material	Acrylonitrile butadiene styrene (ABS)	
Glow Wire Test according to IEC 60695-2-12	650 °C	
Mercury content	0.0 mg	

Application & Mounting

Ambient temperature range	-20+40 °C
Type of protection	IP44
Dimmable	Yes
Type of dimming	Bluetooth
Mounting type	Ground spike
Application environment	Outdoor
Adjustable	Yes
With light source	Yes

Lifespan

Lifespan L70/B50 at 25 °C	15000 h
Number of switching cycles	1000

BATTERY

Type of Battery	Lithium ion
Battery size [GMS]	18650
Number of included batteries	1

Nominal voltage of battery	3.7 V
Nominal capacity of battery	1500 mAh
Battery charging time	8 h

Certificates & Standards

CE / UKCA
No
No

Additional product data

Product remark	Reset settings to default by switching the product on for three seconds and off for three seconds and repeating this five times.
	1 0

EQUIPMENT / ACCESSORIES

- For control via SMART+ App, a smartphone or tablet is required (with minimum Android 8.0 or iOS 14.0)

Safety advice

- If the battery compartment (if applicable) does not close securely, stop using the product and keep it away from children. If you think batteries might have been swallowed or placed inside any part of the body, seek immediate medical attention.

– Please avoid: Maximal ambient temperature: +35 °C. Replacement of a battery with an incorrect type that can defeat safeguard (for example, in the case of some lithium battery types). Altitude during operation: 2000 m. Disposal of a battery into fire or a hot oven, or mechanically crushing or cutting of a battery, that can result in an explosion.

DOWNLOAD DATA

	Documents and certificates	Document name
PDF	User instruction / safety instructions	SMART+ SOLAR SPOT LIGHT
PDF	Legal information	Legal insert SMART OUTD ENDURA SOLAR WORKLIGHT BAT
PDF	Declarations of conformity	SMART OUTD BT SOLAR RGBTW
PDF	Declarations of conformity UKCA	SMART OUTD BT SOLAR
PDF	EU Data Act	SMART Bluetooth Mesh Lighting Products

LOGISTICAL DATA

Product code	Packaging unit (Pieces/Unit)	Dimensions (length x width x height)	Gross weight	Volume
4058075763883	Folding box 1	102 mm x 187 mm x 204 mm	564.00 g	3.89 dm ³
4058075763890	Shipping box 4	390 mm x 215 mm x 230 mm	2685.00 g	19.29 dm ³

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

References / Links

- Further information and frequently asked questions (FAQs) at www.ledvance.com/consumer/smart/faq

DISCLAIMER

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.