

PRODUCT DATASHEET LINK TIME CONTROLLER 1A BLE

LEDVANCE LINK™ TIME CLOCK MODULE | LEDVANCE LINK Time Clock Modules



Product features

- Commission and configure with LEDVANCE LINK™ app
- Control using either the LEDVANCE LINK $^{\mbox{\tiny TM}}$ app or the wireless controller
- Grouping and Zoning: Wirelessly group luminaires to act in sync with each other
- Scene Control: Preset various scenes for individual or group of luminaires using the app and/or wireless/wired controllers
- QR Code for Admin/Guest control: Using the LEDVANCE LINK™ app, Admin and Guest QR codes for each zone can be generated. Allows
 copying the settings to another phone/tablet by scanning this QR code
- Allows setting time-based schedules and high-end and low-end trim through the LEDVANCE LINK™ app

TECHNICAL DATA

Electrical data

Nominal wattage	360.00 W
Nominal voltage	120277 V
Mains frequency	5060 Hz

Dimensions & Weight

Length	73.66 mm
Width	29.21 mm
Height	15.49 mm
Product weight	22.00 g

Capabilities

Dimmable	Yes

Certificates & Standards

Protection class	П
Type of protection	IP66

DOWNLOAD DATA

	Documents and certificates	Document name
POF	Extended installation guide	INSTALLATION GUIDE BLUETOOTH® MESH TIME CLOCK MODULE LEDVANCE LINK
POF	Extended installation guide	INSTALLATION GUIDE BLUETOOTH® MESH TIME CLOCK MODULE LEDVANCE LINKTM
PDF	Extended installation guide	USER GUIDE LEDVANCE LINK FW Manager

LOGISTICAL DATA

Product code	Packaging unit (Pieces/Unit)	Dimensions (length x width x height)	Gross weight	Volume
4099854201196	BAG 1			
4099854182457	Shipping box 100	310 mm x 240 mm x 305 mm	2535.00 g	22.69 dm ³

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

DISCLAIMER

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.